

# WISI VS 83 B

Multiband amplifier



## Description

**WISI Communications GmbH & Co. KG**

Wilhelm-Sihn-Str. 5-7  
75223 Niefern-Oeschelbronn, Germany

Phone: +49 7233 66-280, Fax: -350  
E-Mail: [export@wisi.de](mailto:export@wisi.de)

Technical Modifications reserved. WISI cannot be held liable for any printing error. 3. Juni 2015, 8:51 vorm.

## Technical data

### Downstream

Inputs	4 pcs.
Frequency range input 1	40...108 MHz
Frequency range input 2	160...260 MHz
Frequency range input 3	470...862 MHz
Frequency range input 4	470...862 MHz
Gain input 1	20 dB (input level regulator 0-20 dB)
Gain input 2	20 dB (input level regulator 0-20 dB)
Gain input 3	30 dB (input level regulator 0-16 dB)
Gain input 4	30 dB (input level regulator 0-16 dB)
Output level 1	106 dB $\mu$ V
Output level 2	106 dB $\mu$ V

### Connectors

F-socket	6 pcs.
----------	--------

### General data

Operating voltage AC	230 V
Feeding voltage DC	24 V DC (50mA)
Power consumption	7 W
Screening factor (EMC)	dB Class A, EN 50083-2
Operating temperature range	-10...+65 °C
Protection class	IP20

## Packaging data

Sales unit	1 pcs.
Dimensions (WxHxD) sales unit	16 x 10 x 5 mm
	dm <sup>3</sup>
Gross weight sales unit	0.700 kg
Shipping unit	pcs.
Dimensions (WxHxD) shipping unit	mm
Packaging volume shipping package	dm <sup>3</sup>
Gross weight shipping unit	0.7 kg
	cm
	N
EAN	4010056191559
Article number	19155
Customs tariff number	8543703000